



**OFFICIAL ALEX LOWRY
QA SEAL OF APPROVAL**

Ferrite beads (FB*) function as noise filters and have no resistance.

For PAL Master System II – Based on Master System I audio/composite video circuitry. Remove RF modulator, R27, R28 and R29. Replace R21 with a 75Ω resistor (unnecessary if your SMS2 is from a PAL-B region). Replace C40 with a 10µF electrolytic capacitor. The negative (striped) side should face towards the front on 1990–1992 models.

Alex Lowry

Sheet: /
File: SMS2_Composite_Mod.kicad_sch

Title: Sega Master System II Composite Mod

Size: A5 Date: 2025-03-23
KiCad E.D.A. 9.0.0

Rev: 1
Id: 1/1